


# Cisco Unity Voicemail User Guide

*Use These Keys Anytime During any Changes*

\* Cancel or back-up # Skip or move ahead

## FIRST TIME YOU LOG IN

### To Configure Cisco Unity:

**Step 1** Press the Message button. 

**Step 2** Enter a PIN (password). (Default PIN 12345)

**Step 3** Please follow system instructions for the following:

- Record your name
- Set up a new PIN (password)
- Record your greeting

### To Check Messages from your telephone:

**Step 1** Press the Message button and log on.

**Step 2** Press 1 to hear new messages, or press 3 to review old messages.

**Step 3** Use the following keys to manage your messages and control playback.

### *Use These Keys During a Message*

**0** For help

**1** Repeat

**2** Save

**3** Delete

**4** Slow message playback

**6** Speed up message playback

**7** Skip back

**9** Message Properties

**18** Mark this message urgent

### *Use These Keys After a Message*

**0** For help

**1** Repeat

**2** Save

**3** Delete

**4** Reply

**5** Forward message

**6** Mark it new

**7** Skip back

**9** For message properties

### To Check Messages from outside the office:

**Step 1** Dial **419-589-2600**

**Step 2** When the greeting begins to play, Press \*

**Step 3** Enter your ID (5-digit extension/mailbox number), then press #.

**Step 4** Enter your PIN (password) then press #

### Cisco Unity Voicemail User Guide To Change Your PIN (password):

**Step 1** Press the Message button and log on.

**Step 2** Press 4 >3 >1.

**Step 3** Enter a new PIN (password) and press #.

**Step 4** Enter the new PIN (password) again to confirm it and press #.

### To Change Your Recorded Name:

**Step 1** Press the Message button and log on.

**Step 2** Press 4 >3 >2.

**Step 3** At the tone, record your name, press # to end recording or press \* to keep the current recording.

**To Record a Greeting:**

**Step 1** Press the Message button and log on.

**Step 2** Press 4>1>1.

**Step 3** After Cisco Unity plays your current greeting, press 1 to re-record it, or press 3 to record a different greeting, choose the greeting, and then rerecord it.

**To Enable or Disable a Greeting:**

(You can enable or disable only your alternate greeting by phone.)

**Step 1** Press the Message button and log on.

**Step 2** Press 4 >1 >1.

**Step 3** After Cisco Unity plays your current greeting, press 2 to enable or disable your alternate greeting. Note: When your alternate greeting is enabled, it overrides all other greetings.

**To Reply to a Message:**

**Step 1** After listening to the message, press 4.

**Step 2** Record your reply.

**Step 3** Press # to send the reply, or press 1 for message options.

*Message Options are the same as above.*

**Step 4** Follow the Cisco Unity conversation to handle the original message.

**To Forward a Message:**

**Step 1** After listening to the message, press 5.

**Step 2** Follow the Cisco Unity conversation to address the forwarded message.

**Step 3** Press # to forward the message as is, or press 2 to record an introduction, or press 3 for message options.

**Step 4** Press # to forward the message as is, or press 1 for message options.

*Message Options are the same as above.*

